Rivolta





The benefits at a glance

- High-quality cleaning effect
- Penetrates deposit layers self-actingly
- High flashpoint
- Reduces/prevents manual cleaning expenditure
- High economy



Rivolta

CASSIDA

VITROLIS

antıdot.

Properties

Rivolta S.R.K. is a special pre-cleaner. Our product automatically penetrates and softens, among other things, heavy deposits of carbon abrasion, caked-on dusts, hardened oil and grease layers (oil carbon), loose rust and oxide layers. In many cases, this avoids the need for time-consuming and costly manual cleaning.

Fields of application

Rivolta S.R.K. is used among others to clean diesel engines, heat exchangers, oil coolers, filters, heavy oil filters, oil transformers, gear wheels and chains.

Material compatibility

Rivolta S.R.K. is compatible with metals and most solvent resistant surfaces. However, **S.R.K.** may attack some plastics, elastomers paints and lacquers. Due to the wide variety of processing conditions and applications, we always recommend checking material compatibility first before using it.

Instructions for use

Please spray the parts which are to be cleaned with **Rivolta S.R.K.**, brush the parts or lay the parts in **S.R.K.** Depending on the thickness of the contamination layers the product should act for 10-30 minutes. If **S.R.K.** is absorbed by the contamination layer in the meantime, you should repeat the wetting. When **S.R.K.** has soaked the contamination, you can easily rinse it with **Rivolta S.L.X.** or **Rivolta M.T.X.** cleaners.

Suitable application devices and accessories in our <u>accessories</u> brochure.

Form	liquid			Available in: • cans (10 l and 20 l)
Colour	pale yellow			
Odour	slight	101	20l	

	Value	Norm
Density at 20 °C	0,90 g/cm³	DIN 51757
Flash point	> +60 °C	DIN EN ISO 2719



Bremer & Leguil GmbH

Am Burgacker 30-42 • 47051 Duisburg • Germany Tel. +49 203 99 23-0 • Fax +49 203 2 59 01 info@bremer-leguil.de This text contains facts and statements and is determined with our best knowledge and will be checked continuously. These statements are depending – among other reasons – on experiences gained in the industry. We only pass them on without liability. Before using our products you should test the applicability and you should convince yourself of the satisfactory performance. Our application examples and suggestions should not request to violate patent rights. Product illustrations partly consist of picture compositions and therefore, do not necessarily reflect the reality. V230804